Specifications

| General | |
|---------------------------------|--|
| Frequency Range | VHF: 136-174MHz; UHF: 350-390/400-470MHz |
| Channel Capacity | 99 |
| Channel Spacing | 25KHz/12.5KHz |
| Operating Temperature | -20℃~+60℃ |
| Antenna Impedance | 50Ω |
| Operating Voltage | DC 7.4V(±20%) |
| Battery Capacity | 2200mAh |
| Frequency Stablility | ≤ ± 2.5ppm |
| Dimensions | 60.4(L)*34.6(W)*109(H) mm |
| Weight | 243g (including battery pack) |
| Transmitter | |
| Power Output | H:5W L:1W |
| Modulation | 16KΦF3E(Wide)/8KΦF3E(Narrow) |
| Noise and Harmonic | ≤-36dBm |
| FM Noise | ≤-40 dB |
| Rated Audio Distortion | 0.05 |
| Adjacent Power | ≥65 dB(Wide)/60 dB(Narrow) |
| Modulation Limitation | ≤5KHz(Wide) /2.5KHz(Narrow) |
| Receiver | |
| Sensitivity | ≤ 0.2μV(Wide) /0.25μV(Narrow) |
| Adjacent Selectivity | ≥60 dB(Wide)/55 dB(Narrow) |
| Intermodulation Rejection Ratio | ≥60 dB(Wide)/55 dB(Narrow) |
| Spurious Suppression | ≥60 dB(Wide)/55 dB(Narrow) |
| SNR | ≥45 dB(Wide)/40 dB(Narrow) |
| Rated Audio Output Power | 0.5W |
| Rated Audio Distortion | 0.05 |

Accessories

Standard Accessories





Battery









Charger

Belt Clip

Hand Strap

Optional Accessories

Antenna









Programming Cable



Fujian BelFone Communications Technology Co., Ltd.

Add: A15, Huaqiao Economic Development Zone, Shuangyang, Luojiang, Quanzhou, Fujian, China 36200

Tel: +86 595 28396717 Fax: +86 595 22771635 Email: overseas@belfone.com Website: www.belfone.com









Analog Portable

BF-532 is a professional FM two-way radio with switchable transmitting powers, selectable squelch levels, programmable bandwidth and other advanced analog features. It is designed to deliver more safety and efficiency into your work and life. Its applications range across many fields of work, such as restaurants, warehouses, outdoor activities, etc.

Main Features

- PC Programming
- · Programmable Bandwidth
- CTCSS/CDCSS
- Squelch Levels(0-9)









1 200 2 TO 3 W/S * NO.

www.belfone.com