

BF-OG300

Analog Two-Way Radio

BF-OG300 outdoor Analog radio, balanced fashionable design and practical functions, is equipped with the stylish combination of yellow and black, making the entire design more complete and sense of layers. The rich functions and applications can guarantee the real-time transmission of information, whether it is for emergency rapid calls or daily communication.



Dual Standby

One Key Reply

IP67 Protection

Emergency Alarm

Type-C Charging mode

10 Types Ringtones



FUNCTIONS





- Low Battery Alert
- Keypad Lockout
- CTCSS/CDCSS
- Squelch Level
- Power Saving
- Scan/Monitor/ Beat Frequency
- Dual PTT Key
- 1.25 Inch LCD Screen
- ABS+PC Industrial Material

SPECIFICATION

Frequency Range Channel Capacity Channel Spacing Operating Voltage Battery Capacity	UHF: 400-480MHz 22 25 KHz /12.5 KHz DC 3.7V (±20%)
Channel Spacing Operating Voltage	25 KHz /12.5 KHz
Operating Voltage	
	DC 3.7V (±20%)
Battery Capacity	
	1500mAh
Frequency Stability	≤±2.5 ppm
Antenna Impedance	50Ω
Dimensions (L × W × H)	60 (L) * 33(W)* 121(H)mm
Weight	193g (including battery)
	Transmitter
RF Output Power	≤2W
4FSK Modulation	11K ¢ F3E/16K ¢ F3E
FM Modulation	$\leq \pm 2.5$ KHz/ ± 5.0 KHz
Adjacent Channel Power	60dB
Audio Distortion	<5%
	Receiver
Sensitivity	≤-122dBm (12dB SINAD)
Intermodulation	≥60dB (wide)/ 55dB (narrow)
Adjacent Channel Selectivity	≥60dB (wide)/ 55dB (narrow)
Spurious Response Rejection	≥60dB (wide)/ 55dB (narrow)
Rated Audio Output Power	0.5W
Audio Distortion	≤5%
	Environmental Specifications
Operating Temperature	-20°C ~+60°C
Operating Temperature Storage Temperature	-20°C ~ +60°C -30°C ~ +70°C

Note: The above specification is tested by the trial standard. Due to the continuous development of technology, the data provided are for reference only.

STANDARD ACCESSORIES









Fujian BelFone Communications Technology Co., Ltd

Add: A-15 Huaqiao Economic Development Zone, Luojiang, Quanzhou, Fujian, China

Email: overseas@belfone.com **Phone:** +86 595 28396717 Fax: +86 595 22771635













