



BF-308

Analog Portable Radio

BF-308 is an entry-level analog two-way radio that is cost-effective and feature-rich. Besides a conventional analog feature set, BF-308 comes with two PTT buttons, each with a preset channel. Push PTT button No.1 to initiate a talk on one channel and PTT button No. 2 to initiate another talk on another channel. And of course the user can receive signals from both channels. This is a walkie-talkie designed to deliver maximized convenience at the lowest price.

Main Features

- CTCSS
- Long Battery Life
- Voice Prompt
- 2 PTT Buttons
- Automatic Power Saving
- Busy Channel Lockout (BCL)



SPECIFICATION

General

Frequency Range	UHF: 400–480MHz
Channel Capacity	16
Channel Spacing	25KHz/12.5KHz
Voltage	DC 3.7V (±20%)
Frequency Stability	≤ ±2.5ppm
Antenna Impedance	50 Ω
Battery Capacity	2000mAh
Working Temperature	-20℃—+60℃
Dimensions	58(L)*35(W)*108(H)mm
Weight	195g(battery included)

Transmitter

Output Power	≤3W
Modulation	11KΦF3E/16KΦF3E
Rated Audio Distortion	≤5%
Adjacent Power	60 dB
Modulation Limitation	≤5KHz(width)/2.5KHz(narrow)

Receiver

Sensitivity	≤-123dBm (12dB SINAD)
Adjacent Selectivity	≥60dB(width)/ 55dB (narrow)
Intermodulation Rejection	≥60dB(width)/ 55dB (narrow)
Spurious Suppression	≥60dB(width)/ 55dB (narrow)
SNR	≥40B(width)/ 35dB (narrow)
Rated audio output power	0.5W
Rated audio distortion	≤5%

STANDARD ACCESSORIES



Antenna



Battery



Charger




Belt Clip



Hand Strap


OPTIONAL ACCESSORIES



Earpiece



Programming Cable



Remote Speaker

Fujian BelFone Communications Technology Co., Ltd

Add: A-15 Huaqiao Economic Development Zone, Luojiang, Quanzhou, Fujian, China

Email: overseas@belfone.com

Phone: +86 595 28396717

Fax: +86 595 22771635



Dedicated to increasing the efficiency and reliability of missioncritical communications, BelFone is always on the way to offer responsive, flexible and reliable products. For more information about our products and solutions, contact us or visit us at www.belfone.com.

