

# OG306 ULTRA-SLIM

**Analog Two-Way Radio** 



























# Compact but Modern Design

OG306, with its ultra-slim design of only 16.6mm and extremely tough lines, not only enhances portability but also conforms to modern trends, making it easy for people of all ages and genders to handle. And OG306 is equipped with a toggle channel switch button and a hidden LED matrix display with an integrated screen-off design, ensuring users can clearly see the terminal status, switch channels smoothly and operate normally under the messy lights.



# **Intelligent Noise Reduction**

OG306 is equipped with advanced intelligent noise reduction technology that effectively filters out environmental noise, extracts human voice, and processes audio signals in real time, to guarantee clear and effective communications in any environment.



# **Outdoor-Friendly**

OG306 is an outdoor–friendly radio that supports listening to FM radio. Outdoor enthusiasts such as campers and hikers can listen while moving, easily solving the boredom of outdoor time. Not only that, the reset key can rapidly solve the sudden failure of the radio. It restores basic communication functions without requiring professional maintenance, ensuring outdoor communications remain uninterrupted.



# **Emergency Alarm**

In the event of an emergency or when personal safety is threatened, OG306's emergency alarm function promptly sends high-priority alarm signals and real-time location information to teammates or the command center. It will guide rescue personnel to arrive swiftly, ensuring you are never alone in any dangerous situation.



### **Channel Copy**

OG306 Channel Copy function eliminates the hassle of computer programming. Within seconds of powering on, it can rapidly replicate frequency and establish multi-user communication, with simple and efficient operation that streamlines team coordination.



#### **Bluetooth Connection (Optional)**

OG306 supports Bluetooth 5.0, which not only supports connecting Android mobile phone APP for radio Settings, but also supports connecting Bluetooth headphones and other devices for audio transmission and real-time calls.



#### Long Battery Life

OG306 features a built-in 2200mAh large capacity Lithium battery, providing long-lasting battery life: it can be used continuously for up to 12 hours and has a standby time of up to 25 hours, eliminating frequent charging. Equipped with a mainstream Type-C interface, OG306 supports charging across multiple scenarios, ensuring you can recharge any time during critical tasks or outdoor work. Stay composed and confident, free from any battery anxiety.

# **GENERAL FUNCTIONS**

- VOX
- Reset Kev
- APP Programming
- Busy Channel Lockout
- Voice Broadcast
- Battery Saving Mode
- CTCSS/DCS
- Scan/Monitor
- Low Battery Alert

# **SPECIFICATION**

General		
Frequency range	UHF:400-480 MHz	
Channel capacity	≤ 125	
Zones	1	
Channel spacing	12.5KHz/25KHz	
Operating voltage	DC 3.8V	
Battery capacity	2200mAh	
Battery Life (5/5/90)	12 hours	
Frequency stability	≤ ± 2.5ppm	
Antenna impedance	50 Ω	
Dimensions (L×W×H)	52.7 (L) *16.6 (W) *115 (H)mm	
Weight	137g (including battery)	
Bluetooth (optional)	BT5.0	
Transmitter		
RF output power	≤ 2W	
Modulation mode	11K	
Modulation Limiting	≤ ± 2.5KHz / ± 5.0KHz	
Adjacent channel power	<-60dB	

Receiver		
Analog sensitivity	≤-123dBm (12 dB SINAD)	
Intermodulation	≥60dB(wide)/ 55dB (narrow)	
Adjacent channel selectivity	≥60dB(wide)/ 55dB (narrow)	
Spurious response rejection	≥60dB(wide)/ 55dB (narrow)	
Rated audio output power	0.5W	
Rated audio distortion	≤5%	

Environmental		
Operating temperature	-20℃-+60℃	
Storage temperature	-30℃—+85℃	
Shock & Vibration	MIL-STD-810C/D/E/F Standard	

#### STATEMENT:

- 1. Due to continuous product improvement, the technical parameters and functional features may not be consistent with the actual product. Please refer to the actual product. If there is any change, we will not notify you separately. Please understand.
- 2. If you have other questions about this product or the content of this document is not detailed enough, please contact us.

# **STANDARD ACCESSORIES**









# Fujian BelFone Communications Technology Co., Ltd

Add: A-15 Huaqiao Economic Development Zone, Luojiang, Quanzhou, Fujian, China

Email: overseas@belfone.com **Phone:** +86 595 28396717 Fax: +86 595 22771635

Dedicated to increasing the efficiency and reliability of missioncritical communications, BelFone is always on the way to offer responsive, flexible and reliable products. For more information about our products and solutions, contact us or visit us at www.belfone.com.













